

Claims

AI

9. ~~1.~~ A circuit arrangement for generating square pulses,
5 having an edge-triggered flip-flop (1) and at least one
comparator (2), whose output is connected to the trigger input of
the flip-flop (1), and an energy-storing element (3), which is
charged in alternation as a function of the switching state of
the flip-flop (1), and at least one switching threshold resistor
10 (4) is connected in series with the energy-storing element (3),
at which resistor a voltage generated by the current flowing
through the energy-storing element (3) drops, which voltage is
fed to the signal input of the comparator (2), characterized in
that the energy- storing element (3) is disposed in the
15 transverse branch of a bridge, in each of the four bridge
segments of which a respective switch (7, 8, 9, 10) is disposed,
and the switches (7, 8, 9, 10) are each connected in pairs in
crossover fashion (7, 10 and 8, 9, respectively) by the flip-flop
(1), so that the current flow in the transverse branch is
20 reversible, and that the bridge is connected in series with the
switching threshold resistor (4), and the junction point of the
bridge to the switching threshold resistor (4) is connected to
the signal input (2a) of the comparator (2).

25 10. ~~2.~~ The circuit arrangement of claim ⁹~~1~~, characterized in
that the energy-storing element (3) is an inductive resistor.

11. ~~3.~~ The circuit arrangement of claim ⁹~~1~~, characterized in
that the inductive resistor (3) is a magnetic field probe (12).

30 12. ~~4.~~ The circuit arrangement of claim ⁹~~1~~, characterized in
that the magnetic field probe (12) is used to detect the magnetic

^{13,}
~~5.~~ The circuit arrangement of claim ⁹~~1~~, characterized in that the comparator (2) is an analog comparator, which as its output signals furnishes digital signals.

15. ⁹
~~7.~~ The circuit arrangement of claim ~~1~~⁹, characterized in that the switches (7, 8, 9, 10) are MOSFETs, of which two (9, 10) are triggered directly and two (7, 8) are triggered via inverters (5, 6) from the outputs (1a, 1b) of the flip-flop (1).

16 8. The circuit arrangement of claim 9, characterized in that in the transverse branch of the bridge, a series resistor (11) is connected in series with the energy-storing element (3).